



Electrical:

Frequency Range:	4.0 - 6.0 MHz
Insertion Loss:	3.5 dB Max
Phase Shift:	360 degree Min
Control Voltage:	0-10 Vdc Max
VSWR Input:	1.80:1 Max
VSWR Output:	1.80:1 Max
Input Power:	+5 dBm Max

Specifications:

SigaTek

423 Black Oak Ridge Rd.
Wayne, NJ 07470
Ph: 973-706-8475, Fax : 973-832-4435
www.sigatek.com

SF35A7

Analog Phase Shifters

Dimensions are in inches and (mm)
Decimal Tolerance:
2 place \pm 0.020
3 place \pm 0.010

CAGE CODE : 69UC1

SCALE:N/A

REV
N/A

Notes: All dimensions are typical unless they are specified.
Specifications are subject to change at any time without any notice.
Copy or distribution of this drawing is prohibited.