



## Electrical:

Frequency Range:	200.0 - 400.0 MHz
Insertion Loss:	2.5 dB Max
Phase Shift:	180 degree Min
Control Voltage:	0-20 Vdc Max
VSWR Input:	1.80:1 Max
VSWR Output:	1.80:1 Max
Input Power:	+5 dBm Max

## Specifications:

# SigaTek

423 Black Oak Ridge Rd.  
Wayne, NJ 07470  
Ph: 973-706-8475, Fax : 973-832-4435  
www.sigatek.com

SF54A2

Analog Phase Shifters

Dimensions are in inches and (mm)  
Decimal Tolerance:  
2 place ± 0.020  
3 place ± 0.010

CAGE CODE : 69UC1

SCALE: N/A

REV  
N/A

Notes: All dimensions are typical unless they are specified.  
Specifications are subject to change at any time without any notice.  
Copy or distribution of this drawing is prohibited.