) [25.40]		[31.75] [25.40] I RF Out Q 4 x	0.625 [15.87]	
				\ SMA	CONNECTOR _ACES
Electrical:	Specifica	tions:		\SMA 4 Pl	_ACES 423 Black Oak Ridge Rd.
Frequency Range: LO	10-11	Mhz		\ SMA	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range: LO Frequency Range: RF	10-11 10-11	Mhz Mhz		\SMA 4 Pl	_ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470
Frequency Range: LO Frequency Range: RF Frequency Range: IF	10-11 10-11 DC-5	Mhz Mhz Mhz		SigaTek	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level:	10-11 10-11 DC-5 +10 to +13	Mhz Mhz Mhz dBm	Тур	\SMA 4 Pl	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss:	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5	Mhz Mhz Mhz dBm dB	Тур Тур / Мах	SigaTek	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss: Side Band Rejection:	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5 30	Mhz Mhz Mhz dBm dB dB	Typ Typ / Max Min	SigaTek QM10A10	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss: Side Band Rejection: Carrier Rejection:	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5 30 30	Mhz Mhz dBm dB dBc dBc	Typ Typ / Max Min Min	SMA 4 Pl SigaTek QM10A10 Dimensions are in inches and (mm)	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator SMA Connectors
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss: Side Band Rejection: Carrier Rejection: Input 1 dB Compression:	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5 30 30 30 +5	Mhz Mhz dBm dB dB dBc dBc dBc dBm	Typ Typ / Max Min Min Typ	SMA 4 Pl SigaTek QM10A10 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss: Side Band Rejection: Carrier Rejection: Input 1 dB Compression: Low side is Rejected when C	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5 30 30 +5 Q-port is +90 degre	Mhz Mhz dBm dB dB dBc dBc dBc dBm	Typ Typ / Max Min Min Typ	SMA 4 Pl SigaTek QM10A10 Dimensions are in inches and (mm) Decimal Tolerance:	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator SMA Connectors
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss: Side Band Rejection: Carrier Rejection: Input 1 dB Compression:	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5 30 30 +5 Q-port is +90 degre	Mhz Mhz dBm dB dB dBc dBc dBc dBm	Typ Typ / Max Min Min Typ	SMA 4 Pl SigaTek QM10A10 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010 Notes: All dimensions are typical unless	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator SMA Connectors CAGE CODE : 69UC1 they are specified.
Frequency Range: LO Frequency Range: RF Frequency Range: IF LO Power Level: Conversion Loss: Side Band Rejection: Carrier Rejection: Input 1 dB Compression: Low side is Rejected when C Input Two-Tone Third Order Intercept Point:	10-11 10-11 DC-5 +10 to +13 7.5 / 8.5 30 30 +5 Q-port is +90 degre +15	Mhz Mhz dBm dB dBc dBc dBc dBc dBm	Typ Typ / Max Min Min Typ o I-port	SMA 4 Pl SigaTek QM10A10 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010 Notes: All dimensions are typical unless to Specifications are subject to cha	ACES 423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com I, Q Side Band Modulator SMA Connectors CAGE CODE : 69UC1