			5 DEEP LACES	
	7.2	43 ت	LUAD UT 1000	
		[1.693]	ACES	
Electrical:	Specificatio		SigoTolz	423 Black Oak Ridge Rd. Wayne, NJ 07470
Electrical: Frequency Range:	2.0 – 18.0	ns: Ghz	SigaTek	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range: Coupling:	2.0 – 18.0 10.0 ± 1.00	NS: Ghz dB	SigaTek	Wayne, NJ 07470
Frequency Range: Coupling: nsertion Loss:	2.0 – 18.0 10.0 ± 1.00 1.00	NS: Ghz dB dB Max		Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range: Coupling: Insertion Loss: Coupling Flatness	2.0 - 18.0 10.0 ± 1.00 1.00 ± 0.8	NS: Ghz dB dB Max dB Max	SigaTek SC1017116	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range: Coupling: nsertion Loss: Coupling Flatness Directivity:	2.0 - 18.0 10.0 ± 1.00 1.00 ± 0.8 12	NS: Ghz dB dB Max dB Max dB Max dB Min		Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: nsertion Loss: Coupling Flatness Directivity: /SWR:	$2.0 - 18.0$ 10.0 ± 1.00 1.00 ± 0.8 12 $1.50:1$	NS: Ghz dB dB Max dB Max dB Min Max	SC1017116	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward	$2.0 - 18.0$ 10.0 ± 1.00 1.00 ± 0.8 12 $1.50:1$ 25	NS: Ghz dB dB Max dB Max dB Max dB Min Max Watts	SC1017116 Dimensions are in inches and (mm)	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected:	$2.0 - 18.0$ 10.0 ± 1.00 1.00 ± 0.8 12 $1.50:1$ 25 10	NS: Ghz dB dB Max dB Max dB Max dB Min Max Watts Watts Watts	SC1017116	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected: Power Peak:	$2.0 - 18.0$ 10.0 ± 1.00 1.00 ± 0.8 12 $1.50:1$ 25 10 3	NS: Ghz dB dB Max dB Max dB Min Max Watts Watts Watts KW	SC1017116 Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected: Power Peak: Weight:	$2.0 - 18.0$ 10.0 ± 1.00 1.00 ± 0.8 12 $1.50:1$ 25 10 3 $1.4 / 39.7$	NS: Ghz dB dB Max dB Max dB Max dB Min Max Watts Watts Watts KW Ounces / grams	SC1017116 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected: Power Peak: Weight:	$2.0 - 18.0$ 10.0 ± 1.00 1.00 ± 0.8 12 $1.50:1$ 25 10 3	NS: Ghz dB dB Max dB Max dB Max dB Min Max Watts Watts Watts KW Ounces / grams	SC1017116 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB CAGE CODE : 69UC1
Frequency Range: Coupling: nsertion Loss: Coupling Flatness Directivity: /SWR: Power Forward Power Reflected: Power Peak:	2.0 - 18.0 10.0 \pm 1.00 1.00 \pm 0.8 12 1.50:1 25 10 3 1.4 / 39.7 -40°C to +85°C d VSWR better thar	NS: Ghz dB dB Max dB Max dB Max dB Min Max Watts Watts Watts KW Ounces / grams	SC1017116 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010 Notes: All dimensions are typical unle	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB CAGE CODE : 69UC1