SMA 3 PL4 0,220 [5				.650 [16.5] MAX .500 [12.7] .500 [12.7]
Electrical:	Specificatio		SigaTek	423 Black Oak Ridge Rd. Wayne, NJ 07470 Pb: 073 706 8475 For: 073 833 4435
Frequency Range:	Specificatio 4.0 – 12.4 10.0 ± 1.00	ons: Ghz dB	SigaTek	
Frequency Range: Coupling: Insertion Loss:	4.0 – 12.4 10.0 ± 1.00 0.50	Ghz dB dB Max		Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: Insertion Loss: Coupling Flatness	4.0 – 12.4 10.0 ± 1.00 0.50 ± 0.30	Ghz dB dB Max dB Max	SigaTek SC1030120	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity:	4.0 – 12.4 10.0 ± 1.00 0.50 ± 0.30 17	Ghz dB dB Max dB Max dB Min		Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR:	$4.0 - 12.4$ 10.0 ± 1.00 0.50 ± 0.30 17 $1.30:1$	Ghz dB dB Max dB Max dB Min Max	SC1030120	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward	$4.0 - 12.4$ 10.0 ± 1.00 0.50 ± 0.30 17 $1.30:1$ 50	Ghz dB dB Max dB Max dB Min Max Watts	SC1030120 Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected:	$4.0 - 12.4$ 10.0 ± 1.00 0.50 ± 0.30 17 $1.30:1$ 50 10	Ghz dB dB Max dB Max dB Min Max Watts Watts	SC1030120 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected: Power Peak:	$4.0 - 12.4$ 10.0 ± 1.00 0.50 ± 0.30 17 $1.30:1$ 50 10 3	Ghz dB dB Max dB Max dB Min Max Watts Watts Watts KW	SC1030120 Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dB
Frequency Range: Coupling: Insertion Loss: Coupling Flatness Directivity: VSWR: Power Forward Power Reflected: Power Peak: Weight:	$4.0 - 12.4$ 10.0 ± 1.00 0.50 ± 0.30 17 $1.30:1$ 50 10 3 $0.8 / 22.7$	Ghz dB dB Max dB Max dB Min Max Watts Watts Watts KW Ounces / grams	SC1030120 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dE CAGE CODE : 69UC1
Frequency Range: Coupling:	$4.0 - 12.4$ 10.0 ± 1.00 0.50 ± 0.30 17 $1.30:1$ 50 10 3 $0.8 / 22.7$ $-40^{\circ}C \text{ to } +85^{\circ}C$	Ghz dB dB Max dB Max dB Min Max Watts Watts Watts KW Ounces / grams	SC1030120 Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010 Notes: All dimensions are typical unl	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com Directional Coupler 10 dE CAGE CODE : 69UC1