

Electrical: Frequency Range: Insertion Loss:	Specific DC-12.4 6+1.00	cations: Ghz dB Max	SigaTek	423 Black Oak Ridge Rd. Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Amplitude Balance: Isolation:	0.4	dB Max dB Min	SP10R2F	2-way Resistive Power Divider
Phase Balance: VSWR Input: VSWR Output: Power dividing at	3.0 1.30:1 1.30:1 0.5	Deg. Max Max Max Watts Max	Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020 3 place +- 0.010	CAGE CODE : 69UC1
input:	0.0	vvallo ivia	Notes: All dimensions are typical unless they are specified.	

Specifications are subject to change at any time without any notice. Copy or distribution of this drawing in not allowed without Sigatek's approval.

Splitting loss for 2-way resistive divider is 6.0 dB